




Aluminum 17" Screw Guide




↓


 RAM (memory door)
3 Phillips screws


 Upper Case bottom (red)
3 Phillips


 Upper Case bottom (orange)
1 T8 Torx

↓

 Upper Case bottom (yellow)
1 T8 Torx

 Upper Case bottom (green)
3 Phillips

 Upper Case bottom (blue)
2 Phillips

 Upper Case (sides)
8 Phillips

↙ ↘





To organize your screws, simply place each screw in the appropriate box as you remove them from your laptop.


If you are not planning on immediately reassembling your laptop, you may want to tape the screws to this paper.

Due to model variations, the screws you remove may differ slightly from this guide.


↓

 Keyboard
14 Phillips


 Hard Drive
4 T8 Torx (3 long, 1 short)


 HD Replacement
4 Phillips


↓

 Sound Card
2 T8 Torx

↓


 SuperDrive
3 T8 Torx


 SuperDrive
1 T8 Torx


 PRAM Battery & USB Board
3 T8 Torx


↓






Modem
3 4mm nuts



PC Card Cage (right)
2 Phillips


PC Card Cage (left)
2 Phillips


Bluetooth
1 Phillips


Speakers
2 T8 Torx


DC-In Board
2 T8 Torx



Logic Board (red)
4 T8 Torx





To organize your screws, simply place each screw in the appropriate box as you remove them from your laptop.


If you are not planning on immediately reassembling your laptop, you may want to tape the screws to this paper.


Due to model variations, the screws you remove may differ slightly from this guide.



Logic Board (orange)
3 T8 Torx



Logic Board (yellow)
4 T8 Torx


Display (plastic brackets)
2 T6 Torx


Display (inner)
4 T6 Torx


Display (outer)
4 T6 Torx


Heat Sink & Fan Assembly
6 T8 Torx


Heat Sink & Fan Assembly
1 T8 Torx

